Setting up the FRITZ!Box 6850 5G for use on POST mobile network



Before power up first insert the SIM card in the FRITZ!Box 6850 5G (mini SIM only, red frame)



Insert the **SIM card** into the slot with the slanted edge of the card on the left and the contacts facing downwards.





Screw the antennas to the antenna SMA sockets "Ant1" and "Ant2" on the FRITZ!Box 6850 5G





When using LAN connection on laptop/desktop

connect the LAN cable between FRITZ!Box 6850 5G LAN1/2/3/4 and desktop/laptop LAN.

Device Data on the Type Label

	WI-Finetwork (SSID) FRITZ!Box 6850 WI WI-Fipassword (WPA2) 3779 8981 1562 8	FRITZIBox password W afbecd1234 4 981 1234 Article no 9 2000 2928	Wi-Fi access
	Serial no. H515.123.45.678.901 CWMP account 00040E-123456789012	IMEI 12345678-901234-5 Power units: 311P0W134, 311P0W165 12V 2,5A = 0	AVM GmbH, 10547 Berlin
1 2	Meaning		

- 3 Name of Wi-Fi network (SSID)
- 4 Password of the FRITZIBox user interface
- 5 QR Code to Access Wi-Fi
- 6 Network key (Wi-Fi password) 7 Power adapter specification
- 8 Serial number
- 9 Article number

When connect with Wi-Fi between FRITZ!Box 6850 5G and Laptop/ desktop:

- Click on the Wi-Fi icon in the taskbar. A list appear on the screen showing all Wi-Fi networks
- Select the wireless network of your FRITZ!Box 6850 5G
- Enter the network key (6) and click on "Connect"



After connecting with Wi-Fi / LAN to the FRITZ!Box 6850 5G, open **User Interface** on web browser <u>http://fritz.box</u>

 C A A Not secure fritz.box 	
Firit72	FRITZ!Box 6850 5G
	Welcome to your FRITZIBox
	Please log in using your password. FRITZ!Box password
	Note:
	The FRITZIBox user interface is protected with an individual password ex works. This password is printed on the sticker on the underside of your FRITZIBox.
	Forgot your password? Log In

Fill in the **Password** for user interface (4)



Next step is insert the **PIN code** from the SIM card

🗖 🔶 FRITZIBox 6850 5G	× +					
	ure fritz.box					
Forty I	FRITZ!Box	c 6850 5G				
	Configuring internet access					
	Enter the PIN for yo PIN	our SIM card.	attempts remaining 3 of 3			



Select Internet provider POST LUXEMBOURG





FRITZIBox 6850 5G	× +	
C Q A Not sec	ure fritz.box/#	
EphrZ	FRITZ!Box 6850 5G	
	Configuring internet access	
	Summary of the settings for the internet connection	
	Internet service provider	POST LUXEMBOURG
	Check the internet connection after saving	
	Click on "Next" to save and check the information on the internet connection.	



÷.

FRITZIBox 6850 5G	× [+	
C A Not secure	fritz.box/#	
	FRITZ!Box 6850 5G	
FRITA	Save the Settings	
		The internet connection check was successful.
	-10 -	
	Check for latest updat	te
🔶 FBITZIBox 6850 5G	x +	
C A Not secure	A introduction of the second seco	
FRITZ!	FRITZ!Box 6850 5G	
	Update Check	
		Your FRITZ!OS is up to date.
	- 11 -	
	Configuration Conclud	led
	Configuration Concludes	4
	Configuration Concluded	d
	Configuration Concluded	d
	Configuration Concluded Configure the Internet Connection Configure Telephony	d
	Configuration Concluded Configure the Internet Connection Configure Telephony Wi-Fi Settings	d
	Configuration Concluded Configure the Internet Connection Configure Telephony Wi-Fi Settings Stay Informed	d
	Configuration Concluded Configure the Internet Connection Configure Telephony Wi-Fi Settings Stay Informed Check Update	d
	 Configuration Concluded Configure the Internet Connection Configure Telephony Wi-Fi Settings Stay Informed Check Update 	finished



FRITZ:Box 6850 5G	× +									-	D	×
C A Nots	ecure fritz.box/#						A ^k Y	à 11	6			Ь
EptrZ:	FRITZ!Box	6850 5G				FRITZINAS	•	tyFR(TZ)				
- Contraction	Overview											1
Overview	Model: FRITZIBox	: 6850 5G		FRITZIOS: 07.	30 - Version up to d	ate						
Internet				December 201								
Telephony	Connections			Interfaces			522.2				_	
Home Network	Containvet.	Provider: POST LUXEMBOURG connected since 24.05.2023, 11:25		Mobile LAN	connected 1, 1,40 not connected	Gbit/s † 234,	0 Mbit/s					
Wi-Fi	O Takahasar	Throughput: 1 1,40 Gbit/s † 234,0 Mbit/s		\varTheta WI-FI	on, Wi-Finetwor	k (2.4/5 GHz);	FRITZ:Bo	x 6850 MD				
Smart Home	C mapping	un confinementario a zonnificana		O USB	no device conner	cted						
Diagnostics	Calls today: 0		more	Answering Ma	achine today:0					п	iore	
System	No calls			Answering ma	chine disabled							
Wizards	Home Network	mabled:3	more	Convenience	Features						_	
	O2-2426	Wi-Fi - 5 GHz		Telephone boo	ak 1 telepho	ne book four	d					
	@ PC14-781	WI-FI - 5 GHz		Storage (NAS)	5 MB use	d, 86 MB free						
	iPad	Wi-Fi - 5 GHz										



Model: FRITZ!Box 6850 5G Current power consumption: 47 %

